



Electric Fencing 101

Electric Fencing Systems Design, Installation
and Maintenance



Disclaimer: While every effort has been made to ensure accuracy, neither Gallagher Group Limited or any employee of the company will be liable on any ground whatsoever to any party in respect of decisions or actions they may make as a result of using this information.

In accordance with the Gallagher policy of continuing development, design and specifications are subject to change without notice.

Electric Fencing 101

Contents

Why Use Electric Fencing?	04
Getting Started	08
Powering Your Fence	09
Fence Construction	19
Permanent Fencing	20
Offset Fencing	32
Temporary & Portable Fencing	34
Safety	42
Troubleshooting	44

Why Use Electric Fencing?




- Keep domestic animals in
- Keep wild animals out
- Separate different groups of animals
- Allow rationing of crops and pastures
- Fence off eroding areas, trees, rivers and roads

Why Use Electric Fencing?

How Electric Fencing Works

A short, safe and memorable shock to create a psychological as well as a physical barrier.



At a basic level electric fencing is **more effective at containing domestic animals livestock/excluding wildlife than traditional fencing** due to the fact that the short, safe and memorable shock creates a psychological as well as a physical barrier.

A pulsed electric current is sent along the fence wire, from an energizer which is grounded. When the animal touches the fence it completes the circuit between the fence and the ground receiving a short, sharp - but safe shock. The shock is memorable enough that the animal never forgets.

An electric fence is a psychological barrier, so it doesn't need great physical strength. However, it must be well designed and constructed to absorb some pressure from animals, snow and wind. The energizer must have enough power for the length of fence and for the animals being controlled.

Why Use Electric Fencing?



Pasture Management and Rotational Grazing

Beyond just keeping animals in and out, electric fencing is the best way to achieve optimum pasture yield using rotational grazing methods. This approach works by keeping the grass fresh, short and palatable which ultimately leads to increased meat and milk production as well as reduced supplemental feed costs. It involves grazing paddocks in rotation using a combination of permanent and/or temporary fenced grazing areas.

KEY BENEFITS

Effective

Maximize results potential of feed and greatly improve the feed quality and yield.

Efficient

Direct harvesting of grass or fodder crops by animal with the manure returned directly to the soil during the process.

Flexible

Use a combination of permanent & portable fencing to maximize grazing area control.

Why Use Electric Fencing?



KEY CONSIDERATIONS

Achieving optimum pasture growth is a delicate balance. When considering how best to meter out the pasture feed available look at the following:

1. Number & size of grazing areas - grazing specific areas, so other pasture sections are able to rest and re-grow.
2. How many animals to put on that grazing area - efficiently grazing the allocated area.
3. And for how long - graze to desired residual grass height

The combination of these factors determines the rotation length (how many days before the first area in the rotation is grazed again). The optimum rotation length varies significantly depending on the geographical location and time of year.

The more regular the shift (preferably daily or every few days) the more time the pasture spends growing rather than being grazed, leading to greater grass growth and stock carrying capacity.

Where a permanently fenced paddock is further subdivided using portable electric fences the stock are contained by both a front and a back fence. The back fence protects the recently-grazed area to allow it to recover so it can be grazed again sooner.

Subdivision with high stocking density ensures grass is harvested down evenly to the optimum residual length, and that over time manure is spread more evenly over the whole grazing area.

Getting Started

Every electric fence system is made up of a:

- Power System
- Fencing System

Selection of these depends on property size, fencing usage and animal type.



Power System

1. Do you have a reliable power source?
 - Will determine Energizer type – 110v or battery (including solar options)
2. How much fencing are you looking to power?
 - Distance influences Energizer size – and fence construction
3. Location of fence system?
 - Proper Grounding is Crucial to any system. The condition of the Ground and soils will determine your ground field and system set up. e.g. hot ground system for dry, rocky, or sandy soils, that may also require more ground rods.
 - Solar energizer options are perfect for remote locations with good sunshine



Fence System

1. What do you want to achieve with your fencing?
 - Determines permanent and/or temporary subdivision
2. How long do you want it to last?
 - Some products are designed to last well over 10 years while others are warranted under 10 years
3. What animals are you trying to keep in/out?
 - Influences the fence setup like the number of wires & spacing
 - Impacts product choice. For example, horses have special requirements

Powering Your Fence

Energizer Selection

Energizers

All Gallagher Energizers are low-impedance and guarantee a high-energy pulse. Selection is based on power availability, fence length, number of wires, vegetation touching the fence, application (does it need to be regularly moved) and the number of animals (fence pressure).

The only true way to compare different Energizers is based on **STORED JOULES**, it is a constant measure and not affected by variations in fence conditions or grounding.

Stored Joules – How it works

Like horsepower on a vehicle. It is the potential power in the engine to maintain speed no matter what the vehicle is pulling behind, or what the gradient of the road is.

In an Energizer, power from either a 110V outlet or battery source enters the unit and is stored in capacitors. This stored energy is the potential voltage available in the single pulse per second generated when the animal touches the fence. The higher the stored joule rating the greater the Energizer's ability to push past shorts caused by weeds and fence faults, as well as cover future fence expansion.

Gallagher Recommends Always purchase the highest powered Energizer you can afford. More power provides more confidence that the fence will perform despite unexpected shorts like vegetation growth. Also electric fence systems tend to grow, so purchase an Energizer with headroom to power additional future fence.

TERMS

Voltage - an indication of electrical pressure

Current (amps) - an indication of electrical flow

Stored Joules - the amount of energy stored in the energizer

Output Joules - the energy discharged on the fence

Pulse Shape - the measure of the wave of energy traveling down the fence line

Gallagher's range of Energizers continues a proud tradition of the world's best engineered products

1) Indicator lights on all Energizers tell you at a glance that the Energizer is operating

2) All energizers are fitted with lightning protection and are fully modular for rapid servicing and replacement

3) Gallagher's reputation for worldwide service and satisfaction has endured for over 85 years

4) All Gallagher Energizers have a three year warranty.

Powering Your Fence

Energizer Selection

Types of Energizers

110V, Plug-in Energizers are the best choice if you have access to a power outlet. The Energizers are reliable in every situation with exception of a power outage and will provide you with the most power for the least amount of money. You will need to install them inside a structure where they are protected from moisture.



Battery Energizers are typically portable and great for remote areas far from power outlets especially in cases where they are periodically moved. These are powered by our Lithium Energizer range.



Solar Energizers are portable and an excellent choice for temporary fence applications. They are a logical choice for remote areas where there is no 110V outlets. adequate sunlight will keep the battery charged and running.

The solar panel charges the battery by converting light directly into electricity. The battery stores this electricity to operate the energizer. This enables the energizer to operate at night or during periods of low sunlight.



Multi Powered Energizers are designed for you to use in any situation They can be utilized as a 110v plug in, battery only, or Solar.



Powering Your Fence

Energizer Selection

MODEL	STORED JOULES	'UP TO' DISTANCE CLEAN FENCE (MILES/ACRES)	RECOMMENDED DISTANCE TYPICAL FENCE (MILES/ACRES)	I SERIES ADDED FEATURES
-------	---------------	--	---	-------------------------------

Plug-in Energizers

M10000i	100.0	1,000 / 6,000	125 / 3,000	▪
M5800i	58.0	430 / 2,700	87 / 2,200	▪
M1500	15.0	160 / 900	40 / 360	
M1100	11.0	110 / 650	36 / 280	
M800	8.0	90 / 520	30 / 200	
M560	5.6	75 / 400	23 / 130	
M360	3.6	55 / 250	19 / 95	
M160	1.6	30 / 100	11 / 60	
M120	1.2	15 / 60	6 / 30	
M60	0.6	10 / 40	3 / 20	
M30	0.3	5 / 20	2 / 10	
M10	0.1	2 / 10	0.5 / 3	

Multi Power Energizers

MBS2800i	28.0	250 / 1,500	50 / 1,000	▪
MBS1800i	18.0	200 / 1,200	42 / 420	▪
MBS800	8.0	90 / 520	30 / 200	
MBS400	4.0	60 / 280	20 / 120	
MBS200	2.0	45 / 160	14 / 90	
MB150	1.5	30 / 100	11 / 60	

Battery Powered

B60	0.6	15 / 60	5 / 40	
-----	-----	---------	--------	--

All in one Solar

S400	4.0	60 / 280	20 / 120	
S200	2.0	45 / 160	14 / 90	
S100	1.0	30 / 100	8 / 60	
S80 Lithium	0.8	30 / 100	7 / 55	
S60 Lithium	0.6	27 / 90	6 / 40	
S30 Lithium	0.3	20 / 60	4 / 20	
S20 Lithium	0.2	12 / 40	2 / 14	
S12	0.12	4 / 18	0.6 / 6	
S6	0.06	0.74 / -	0.37 / -	

Table is a guide only.

Gallagher Recommends - comparing on stored joules only, since these distance/acreage ratings are always manufacturers estimates because two properties of the same acreage/fence distance may have dramatically different conditions e.g.: number of wires, vegetation growth, stocking intensity.

Powering Your Fence

i Series Fence System

i Series Fence Energizer Systems

The **i Series Energizers** have extremely reliable power that adapts output up or down depending on your fence conditions. Each one also comes with a separate controller that can be mounted outdoors for easy fence performance checks.

ENERGIZER

Reliable and adaptive performance even in extreme conditions



APP GATEWAY

Enable phone-based fence monitoring and real-time energizer control and fault notifications via Bluetooth or WiFi.



ENERGIZER CONTROLLER

Easily monitor and control fence performance



FENCE MONITOR

Create fence zones and monitor fence performance around your property




ENERGIZER REMOTE & FAULT FINDER

Quickly locate and repair faults



ALARM SYSTEM

Secure your assets




Powering Your Fence

i Series Fence System

On i Series models you can also add monitors around the fence line that feed information back to the Controller and tell you if all is well or if there is a fault in their area.

The Remote & Fault Finder helps pinpoint any faults quickly, saving hours hunting for and fixing the issue.

How the System Works:




- 1 Fence Monitor(s) recognize any significant drop in fence zone or Energizer performance and raise alarms.




- 2 Alerts are sent to the Energizer Controller and/or optional Alarm System.



- 3 The Controller and Remote indicate which zone is in fault. The Remote is used to find the fault within the zone.



- 4 Power to the fence at the fault location is turned off using the Remote, allowing a safe and convenient repair.



- 5 Once the fault is repaired, power is restored to the fence and tested using the Remote.

GALLAGHER DEVICES APP

Manage, monitor and control your energizer using your phone via the App Gateway.



Powering Your Fence

Grounding

Grounding Systems

The ground must be as conductive as possible for the fence to give the animal an effective shock. A simple guide is one ground rod for every five joules of stored energy with a minimum of three ground rods.

Follow the recommendation in the chart to get the maximum benefit. When in doubt, add more ground rods. The number of ground rods will vary depending on the power of the energizer and the soil type. High powered energizers need more ground rods than low powered energizers. Dry, sandy, rocky or frozen soil will require more ground rods than wet soils.

Energizer Size	Required Ground Rods
Up to 15 Joules	3 Rods minimum
Up to 25 Joules	5 Rods minimum
Up to 35 Joules	7 Rods minimum

Handy Hint

The rule for ground rods when installing permanent fencing

- | | |
|-------------------------|---|
| 10' Between ground rods | 6' Minimum length of rods |
| 3 Ground rods minimum | 1 Wire connecting all rods to Energizer ground terminal |

As a rule of thumb, use at least 3 ground rods or the Energizer Stored Joules rating divided by 5.

Why does the Energizer need a ground system?

The ground is half the circuit of your fencing system. Electrons travel from the energizer, along the fence wires and back through the ground to the Energizer to complete the circuit. Like a radio antenna collects sound waves, the ground system collects the electrons. The ground must be as conductive as possible for the fence to give the animal an effective shock.


Main causes of a poor ground system are:

- Rusty or corroded ground rods
- Broken ground wire connecting the rods
- Not enough ground rods
- Ground rods too close together or too short
- Poor connections at the rod or in the connecting wire

Powering Your Fence

Grounding


Additionally you will need to setup your electric fence according to how 'green' the area is all year round.



All Live Wire System

- best suited for wetter regions

For use in greener regions with good ground conductivity. All fence wires connect to the red terminal on the Energizer and a shock is delivered to an animal when it's touching the ground and the fence at the same time.



Ground Return Wire System

- best suited for drier regions

For use where the ground struggles to conduct enough power (for year-round dry, frozen or snow conditions). The live & ground wires on the fence create the shock when the animal touches them both at the same time.

Don't	Do
Do not allow bare wires to touch an iron clad building - use double insulated cable	Keep energizer ground system 33-40' away from other electrical ground connections
Do not use rebar for ground rods	Keep energizer ground system 33-40' away from any metal pipes carrying water
Do not use copper lead-out wire or copper ground rods.	Use galvanized ground rods. Rusty or corroded ground rods will not be effective
Do not place near fertilizer, animal urine and manure (corrosion)	Locate rods where soil tends to stay moist, north sides of buildings, low spots
Do not place your ground rods where they are likely to be hit by equipment	When constructing positive/negative fences, re-ground negative wires every 1,200'

Powering Your Fence

Basic Fault Finding

Using a Fault Finder

The current flow on the fence will vary depending on the size of your Energizer, amount of vegetation and the size of your fence system. With time you will learn the normal current flow on your fence.

Fence tools and testers are another useful accessory to have on hand when building, maintaining or checking an electric fence. Gallagher has two fence testers, both available from your local Gallagher Dealer. The Fault Finder is a all-in one device, current meter and fault finder. The Volt Meter measures volts only.

To obtain the best results from your Fault Finder, Gallagher recommends that you check the current while the fence is operating without any faults. Then, when you suspect there is a fault on the fence line, you can compare the current flow with the "normal" current flow.

This will indicate whether a fault exists and, if so, how much the fault is affecting the performance of the fence.

1. The Arrow on the LCD will indicate which direction the current is flowing.

2. Following the direction of the current, take readings approx. every 330' or at junction points along your fence line.

Note: At a junction point, follow the wire with the highest current flow.

3. A fault is indicated by a drop in current flow between two checkpoints. The fault will be somewhere between the two checkpoints.

4. To narrow down location of the fault, work back along the fence checking the current flow at shorter intervals.

5. Correct the fault.

6. After correcting the fault you should see the current reading drop and the voltage group. If not, check for further faults.

See page 50 for more troubleshooting help using a Fault Finder.

HANDY HINT:

Multi-wire fences connected in parallel will have similar current flowing in each wire. To get the total fence current flow, add together the current flow in each wire.

Fence Volt/Current Meter and Fault Finder
G50905



Fence Volt Meter
G503014



Powering Your Fence

Testing Your Power

Testing on All Live Wire Ground System

This should be done once a short section of fence has been built. You should test your system at least once a year at the height of any dry period to ensure the grounding capacity is sufficient for the joule rating of the energizer.

Short the fence out at least 330' away from the ground system by using several ground rods between the wires and the ground. Reduce the fence voltage at this point to 2000V (2kV) or less.

Using a Volt Meter, measure the voltage between the wire connecting through the ground rods to the Energizer ground terminal and an independent ground rod. This rod should be a galvanized metal rod, minimum 8" long. Place the rod 3' away from the ground rods or as far away as your Volt Meter cable will reach.



There should be no reading on the Volt Meter; however, up to 200V (0.2kV) is acceptable. If the voltage is higher than this, switch off the Energizer, drive in more ground rods at the recommended spacings and connect them to the existing ground system until the voltage is down to the acceptable level.

Testing a Ground Return Wire System

Install a 6' ground rod as close as possible to the end of the fence. Install a 500 ohm load tester between a hot wire and ground wire. Choose the location for the ground rod in a damp area if possible. If you cannot find a damp area, the ground test may be unreliable.

Using a Volt Meter, measure the voltage between the hot wire and the ground wire across the load tester you just installed.

Next measure the voltage between the hot wire and the independent ground rod, leaving the load tester in place.

If the second voltage reading exceeds the first by more than 1000V (1kV) check the ground return wire for loose connections.

Finally, connect the independent ground rod to the ground return wire as a permanent connection.

Extra ground rods can be added at various places around the fencing system and connected to the ground return wire to improve ground performance.

If the first voltage reading is less than 3kV, your fence system is at risk of poor animal control.

Assuming that your ground wire return checked out satisfactorily, check that the fence hot wire has good connections. If connections are good, it is possible that your energizer is too small for your fence system. Assess your total length of fence or property size against the energizer selection chart on page 11.

Powering Your Fence

Lightning Protection & Leadouts

Lightning Diverters

Lightning will likely damage your Energizer if it strikes your electric fence. Gallagher Energizers have internal lightning diverters that give partial protection against small strikes.

Since lightning always finds the easiest way to ground, installing a Lightning Diverter will give added protection by providing a path for any lightning that strikes the fence to be diverted to the ground.

Otherwise disconnect the Energizer from the fence and power supply during lightning storms.

Using the diverter does not guarantee complete protection. In bad lightning areas, grounding the top fence wire helps significantly by encouraging the lightning get to ground without passing through the Energizer.

Leadout

Leadout describes the cable and wire that carries the power from the Energizer to the middle of your fence system. It can be either run overhead or underground. Insulated leadout cable should be used to prevent the leadout from shorting out on obstructions or the ground and should be used in buildings, under gateways and where soil could corrode exposed galvanized wire.

This is not so important on small properties, but where medium sized distances of fencing are to be erected (<10 miles), use 12.5 gauge leadout cable. On large properties powering large energizers larger than 20 joules, high conductive cable should be used.

Never use household electrical cable; it is made for a maximum of 440 volts and for inside work only.

Never use Copper wire because of electrolysis. Joining Copper with the Galvanized fencing materials will cause corrosion, decreasing the ability to complete the circuit.

Keep resistance to a minimum and ensure maximum power transfer around your property by choosing the cable with the lowest ohm's rating.

CAUTION

NEVER use household electrical cable. It is made for low voltage use only.

NEVER use copper wire/cable because electrolysis (electrical corrosion) occurs where it joins galvanized wire.

Fence Construction

Selection of the right fencing systems depends on property size, fencing usage and animal type. Use this electric fence guide to help you configure your fence based on your usage and the animal(s) you will be fencing.

1 Permanent Electric Fencing

Permanent electric fences for highly effective animal control that lasts a lifetime.

2 Offset Fencing

Extend the life of an existing conventional non-electric fence by retrofitting an electric wire.



End strain assembly

provides an insulated attachment between the wire and the strainer posts at each end of the fence.

In line straining

allows the fence to be tensioned and re-tensioned as required.

Insulators attach the fence wire to the posts, keeping the wires at the correct spacing and height.




Offsets specific to Offset Fencing, hold the electric wire off the existing non-electric fence wire or posts on a conventional fence line.

3 Temporary/Portable Fencing

Easy to transport, assemble and take down for short-term animal control or rotational grazing.


Reels hold the tape, braid or wire for the portable fence. You can use just one reel for single line fences or up to three reels, attached to a reel stand, for multi-wire fences.

Posts are lightweight yet sturdy. Pigtail and Ring Top posts are most popular for cattle fences and multi-wire treadins are used for all livestock fences.



Power Connectors

are leads that connect a portable fence to an existing permanent electric fence.



Tapes, Wires and Braids are used on portable fences rather than the high tensile galvanized wire used on permanent fences. Gallagher conductors are ideal for portable electric fences as they are light, visible, easy to wind and durable.



1. Permanent Fencing


High tensile wire systems create long life, permanent electric fences. They are easy to install and provide highly effective animal control that lasts.

Permanent fences use highly conductive, corrosion resistant fence wire together with wood, t-posts, fiberglass and Gallagher insulated


line posts, couple with components to keep fences looking good and working effectively for a life time.

Fence Set Ups

Cattle




Pigs, Sheep, Goats



High quality, long lasting electric fences cost less than other traditional fencing options.



Gallagher's Insulated Line Post makes fence construction easy giving a low maintenance and attractive fence.




Animals quickly learn to respect electric fences and keep away – so the fence looks good for longer, and your investment is protected.



Horses are lively and at times unpredictable, so keeping them safely contained is paramount.

A Gallagher equine fence is a safe, reliable and highly visible solution designed to ensure your horses' welfare.

Three options are commonly used for long term equine electric fencing – a permanent fence using the new Equine Fence Wire, semi-permanent Tape or Braid fences.



Equine Fence Wire is the safest, most effective electric fence for your horse. This long life, high tension fence uses specially designed wire coating to reduce risk of injury.



Turbo Braid can be used as a low tension semi-permanent fence alternative to Equine Fence Wire. Braid is designed not to tangle or overstretch and is easy to install.



A semi-permanent Tape fence is highly visible, simple to construct and will last years, making this type of fence an economical and popular choice for horse owners.

Permanent Fence Building

Fence Posts

Choosing Permanent Fence Posts

While the heart of your electric fence is your energizer, fence posts are the backbone of your fence system.

A permanent fence post needs to stand straight and solid for many years. Permanent fence line posts typically have about one third of their length underground, so add half again as much to the height of your fence to determine the post length. End and corner posts typically have as much in the ground as above.

There are three basic types of permanent fence posts: wood, steel, fiberglass.

Wood Posts

Round wood posts provide the basis for a strong permanent power fence. Gallagher offers a range of insulators for attaching electric fence wires to wood posts, including special equine fencing products for Equine Fence Wire, braid and tape. Insulators can be attached to the post using staples, screws or flat head nails.

Posts can be installed by digging a hole and then manually backfilling and tamping the post tight, or by driving the post into the ground using a tractor or trailer mounted post driving machine.

Post spacing depends on the number of wires, wire type and terrain and can vary between 15-30'. Post spacing can be extended if fiberglass or wooden droppers are installed between the posts.

Steel Posts

A steel t-post offers a simple line post alternative to a wood post. Steel posts have the advantage of being able to be installed using a sledge hammer or

manual post driver, reducing the need for expensive post hole diggers or tractor mounted drivers. They can also be driven into hard ground more easily. Gallagher provides t-post insulators that can snap-on to a steel post and hold a fence wire.

Additionally, fence toppers are available for securing a top mounted line post tape or wire. Post spacing is the same as wood posts.

Fiberglass Posts

Fiberglass is a quick and easy option for permanent fences.

Posts are simply driven in the ground using a post driver. Post clips allow for wires to be attached.

These amounts may vary depending on ground contour.

Gallagher Insulated Line Posts

Gallagher now offers an Insulated Line Post. This post is an insulated fiberglass post. A UV protected polyethylene sheath protects the fiberglass core from UV damage and also gives the post the ability to flex when the fence is impacted, preventing broken or bent posts, and minimizing animal injury.

The Insulated Line Post uses a nylon "snap-on" clip to hold wire to the post. A tape clip is also available.

Permanent Fence Building

Fence Tools

Permanent Fence Tools

Below are some useful tools that will be referred to as you continue reading.

Fencing Pliers & Wire Cutter
G52200



Specifically designed for cutting, stripping and bending electric fence wire with minimum wire damage.

Strainer Handle
G69530



Spring loaded ratchet strainer handle for quick adjustment of wire strainers (fits most varieties of ratchet strainers).

Ratchet Wire Tightening Tool
G645004



In line wire tightener handle with super smooth ratchet action, to be used with Gallagher in-line wire strainers (G64304).

Wire Twisting Tool
G523004



Ideal for installing clips on posts and droppers.

4 Groove Wire Crimping Tool
A609



20" Long 4-groove, robust tool for crimping wire joiners and splicing wire.

Pay Out Spi
A304



A necessity for building permanent fence. The adjustable break keeps wire from over-spooling.

Post Driver
G52501



A specially designed driver for the Insulated Line Post.

Tie Down & Handle
G61500 Tie Down
G61501 Handle



Ensures a secure fence tie down. Tie down and handle sold separately

TERMS

Insulator - A non-conductive clip used to attach your wire to a post to prevent power loss.

Clips - Like an insulator, clips hold wire on a post. Clips can be metal or plastic.

Brace - Fences with a lot of tension on the wires are braced at the corners and ends to keep the wire from pulling the corner post over.

Tie-downs - Are anchors to hold wire down in hollows.

Droppers (Stays) - maintain wire spacing between posts on multi-wire

high-tensile electric fencing. Droppers simply rest on top of the ground, and their sole purpose is to maintain vertical wire spacings between posts.

Corner Post & Brace Installation


Properly designed and installed brace assemblies, end and corner posts are keys to building a fence that will last a lifetime.

Plan the fence line. Avoid rough, stony or steep areas if possible. Install corners and ends before adding your line posts.

Set your corner posts in position. A 7' post, 6" in diameter is usually adequate. If you are planning to hang a heavy gate from the post, ensure the post is strong enough. One of the most common mistakes made is that installers do not set their corner, end and brace posts deep enough.

By far, the most common bracing for end and corner posts is the “H” or horizontal brace. The brace has four different parts: the end or corner post being braced, the brace post, the horizontal cross brace that connects the two posts and the brace wire.

The length of the cross brace should be 2 - 2.5 times the height of the fence. Tighten the brace with a diagonal wire that ties the top of the brace post to the bottom of the end or corner post. Recommend at least two wraps of high-tensile wire.



2 - 6" x 84" min, Full treated Wood

Centered at 37" above ground level.
1- 4" x 120" Wood or 1- 2" x
120" Thick Wall Pipe

1 - Permanent Wire Tightener
2 - Joint Clamp
2 - Brace Pins, 12"
High Tensile Wire



Permanent Fence Building

Corner Post & Brace Installation

A variation on the “H” brace is the “N” brace, in which the cross brace runs diagonally from the top of the corner post to the bottom of the brace post, with a bracing wire running in the opposite direction.

Because it’s angled, the cross brace in an “N” brace must be longer than in an “H” brace, which can increase the cost.

Although “H” braces afford optimum strength because they consist of two posts in the ground, it’s not always easy to accomplish - especially if you’re building in rocky soils. When just getting one post in the ground is a challenge, construct a “floating” brace.

This brace also consists of four parts: the post being braced, the brace itself, a brace wire and a brace pad. The assembly works by directing the tension of the fence down the brace.

The most important thing with a floating brace is the angle of the brace. You will need to create a 30-60-90 triangle with the post, brace and wire. The brace should be set at 30 degrees from the ground to the brace and 60 degrees from the post to the brace.

For a brace pad, use either a flat rock or a patio stone; either will allow the brace to disperse pressure into the ground. It’s critical that the post be set deep otherwise the fence tension will jack the post right out of the ground.

Gate openings need consideration as well. Posts may need to be of larger diameter and set deeper depending on the length and weight of the gate that will hang from it.



TIP


Install a temporary fence for a period of time to see if it works for your needs before installing a permanent fence.

Permanent Fence Building


Strainer Installation

Wire Attachment to End Post Assemblies


Mark the wire spacings on the corner posts. Tie the strainers no more than 4" away from the post to prevent animals from pushing through the fence between the post and insulators.




Start with a piece of wire - 3' in length .




Form a knot as shown and slide it firmly against the post.




Finish with a tight tie-off. Wrap the wire 3 times around the strain wire. Cut or break off the remaining wire.



Wind the wire once around the insulator. Bend the wire so that the strain is from the center of the insulator.



Put a 90° bend in the wire about 6" beyond the knot to form a crank handle. Wrap the wire neatly and tightly 6 times around the strain wire.




Grasp the wire just beyond the bend and crank it parallel to the fence line (back toward the post or splice). The wire will snap right off.

Permanent Fence Building

Line Post Installation

HANDY HINT

To save time and effort, purchase a Gallagher Termination Kit. This kit includes pre-assembled insulated wire strainer and wire loops for your end posts, eliminating the need for special tools or wire tying.



Angle Posts

If you need to install angle posts, a 4" post is usually sufficient support. If the angle is not sufficient use inline insulators outside of the post.

On sharper corners, you may have to fasten the hot wire on the inside of the post to prevent it from touching the post.



Install line posts

Use a payout spinner to run out the top and bottom wires as guides for positioning line posts. Use 12.5 gauge high tensile wire for electric fencing because it retains its tension far longer than soft wire. It is reasonably easy to use and conducts enough current for most situations when connected in parallel.

Attach the top and bottom wires to corner insulators and any angle or corner insulators. Leave the tails long enough so they can be used for electrical connections later. Next, tension the wires just enough to provide a straight line for positioning the line posts.

Install line posts on rises or hollows first. As each post is installed, attach the wires to them to help decide the position of the next post in the fence line. On sharp rises, line posts may need a block to prevent the post from sinking while posts in hollows may need to be tied down. Fiberglass posts should only be used in straight lines.

Install the remaining line posts where necessary. On flat or level ground use one post up to every 30'. On hilly or uneven ground, posts will need to be closer together to maintain the wire height.

Run out the remaining wires, tie them off to the end strain insulators and attach them to all the posts.

Permanent Fence Building

Making Wire Connections

Tension the wires

Tension the wires to approximately 200lbs using Permanent Wire Tighteners and a suitable tensioning handle. If wild animal pressure is likely, increase the tension, especially on the bottom wires.


In regions where snow load is a problem or where wildlife may come into heavy contact with the fence, install permanent tension springs to help prevent the wire overstretching. Place permanent wire tighteners in the center of the fence so the wire pulls from both ends.



Electrical connections

Connect all hot wires in parallel at both ends of the fence. This will ensure maximum conductivity. For a three wire fence, bring the tails, previously left long from the top and third wires to the second wire and connect firmly with a Joint Clamp.

Make sure it's tight. Wrap the excess wire around this second wire and beak it off for a smooth finish. Bring the tail from the second fence wire to a Gallagher Cut Out Switch and where necessary break it off. This wiring configuration minimizes the number of joint clamps and creates a clean look.



Permanent Fence Building

Making Wire Connections

TIP

Join wire using a figure eight or reef knot. These will give better electrical contact than a double loop join.



Reef knot





Figure 8 knot



Joint clamps

All other permanent connections should be clamped using Joint Clamps to ensure tight wire connections. Multiple joint clamp options are available.

Gallagher
Recommends –
*re-tightening joint
clamps as part of
a regular spring
fence maintenance
program.*



Cut out switches

Cut out switches are handy for isolating different sections of fence. This is useful when you are looking for faults or carrying out maintenance. Place cut out switches at gateway or junctions where a single or multiple fence line can be turned off.

Connect the undergate cable to one switch terminal and the tail of the second line wire to the other terminal.



Permanent Fence Building

Insulator Selection

Choosing the right insulator for your fence

Gallagher's heavy duty plastic insulators are made from the highest quality polymers infused with UV stabilizer for sun resistance, toughness and durability. Porcelain insulators are fire-resistant and ideal for high fire risk areas.

The type of insulators you require will depend on the type of post and the type of wire that you have selected for your electric fence.

To determine the number of insulators you require: calculate the number of fence posts x the number of strands = number of insulators needed.

For corners and ends, use insulators made specifically to handle the extra wire strain. To determine the number of



corner/end post insulators you require: calculate the number of corner/end posts x the number of wire strands = number of corner/end post insulators needed.

Gallagher offers a range of insulators for attaching electric fence wires to your chosen post.

Wood Post Insulators

The Claw insulator provides a strong permanent attachment system with large shield. Alternatively Pinlock insulator products enable the wire to be temporarily removed from the fence while under tension. For example when wires need to be lowered for temporary vehicle access. Insulators are also available for equine fencing products including for tape and Equine Fence Wire. These are all attached to the post using staples, screws or flat head nails.

Steel Post Insulators

Gallagher manufactures quality double pinlock insulators for attaching electric wires to steel t-posts and y-posts as well as a topper cap for securing a top mounted tape or wire.

Fiberglass Clips

Attach wires to Fiberglass posts using metal clips.

Insulated Line Post Clips

Attach wires or tape to Gallagher Insulated Line Posts using specifically designed insulator clips.

Permanent Fence Building

Gate Installation

Gates and gateways

Gates should be wired so that they are dead when unhooked. Use double-insulated underground wire (placed in a pipe for protection) to run power under the gate - preferably underground.

Seal ends or turn ends of pipe down to keep out moisture. Install the gate with an insulator, and power the gate through the gate handle. Use 1/16" or 1/8" galvanized cable for the gate because it is much more flexible than high-tensile wire.

Where possible, position gateways on flat, firm areas, away from steep banks where erosion could occur. Carry the power (and ground return if you have a ground wire return system) across the gateways preferably underground using double insulated cable in a pipe for protection and simple maintenance. Bury the cable/pipe at least 12" deep and cover with soil that is free of rocks and debris. Connect the cable ends to the fence using join clamps or through a Cut out Switch.


Electrified Gates

Electric gates are low cost, effective and extremely easy to install. Choose from high visibility electrified spring gates, tape gates or bungy gates.

Tape gates provide the most visible gate solution. Choose spring or bungy gates where the gate needs to be stretched across a road to divert animals into the paddock.

CAUTION

Do not rely on electric gates to get power across gateways because when the gates are open power is lost to the fence. Also the conductor in an electric gate is not designed to carry high currents so power will drop even when closed.



2. Offset Fencing


Offset brackets are fitted to a conventional fence with an electrified wire (or wires) on one or both sides of the fence. The wire discourages animals from rubbing or pushing against the fence, thereby extending its life.

A variety of offset brackets are available to attach to wood post or t-post fences, or to mount directly onto the wires of an existing non-electric fence (barbed wire, chain link, etc.).


Once you've chosen your products, see below for the recommended offset electric fence set up for cattle, sheep, pigs, goats and horses.

Fence Set Up


Cattle



Pigs, Sheep, Goats



Horses



Offset electric fencing is an economical and easy to install option if you have an existing or new non-electric fence that you want to protect.



Offsets come in many options including Porcelain. Porcelain insulators will not break down due to sun damage and are resistant to fire.



A side mount ringtop offset is a popular option for wood post fences. Provides complete freedom of the offset wire placement.



Offset wire mounts provide added protection for traditional fences. This protects your fence investment and extends the life of the fence.

Offset Fencing

Selecting Your Offsets

Choosing offset brackets

Conventional fences can be made to last for many more years by attaching offset insulators with an electrified wire on one or both sides of the fence.

Gallagher recommends attaching a single offset wire at two thirds the height of the animal to be controlled. If sheep and cattle are in the same area it is better to use two offset wires (one for sheep, one for cows). However a single wire three quarters the height of the sheep will still protect the fence from both animal types.

If the old fence is tangled or has broken wires, it will need to be repaired. Otherwise you will run the risk of loose non-electric wires causing accidental shorting on the electric offset wire. Change the worst wires and tighten the others where possible.

Mistakes made with an offset fence

The most common error is the use of soft wire for the fence wire and for the offset bracket. High tensile wire should always be used for the fence wire, and only spring steel wire for the offset brackets. The bracket must be able to spring back in place after impact or it will become entangled with the wire of the old fence and short out.

The second most common mistake is the use of brackets that are too short allowing the hot wire to remain too close to the fence it's attached to. Brackets should hold the hot wire 5-12" from the old fence. Some brackets on the market are 4" long or less.

Another important factor: whenever possible offset brackets should not be installed onto the posts of the old fence. They should be installed between posts, or adjacent to the posts if the fence is

Wire offsets are made from galvanized high tensile spring wire, these offsets twist onto existing fence wires.

Wood post offsets are made from galvanized high tensile spring wire. This offset is stapled to wooden posts.

Ringtop offsets are driven into wood posts then stapled in place. For hard timbers, pre-drilling a pilot hole is recommended.

Chain link offsets are made from galvanized high tensile spring wire, this offset twists onto existing chain link wires.

T-post offsets extend 5" and their extra locking tab will fit all t-posts.

sagging badly. Installing between the old posts provides flexibility and lets the wire spring back into position after being impacted by an animal or piece of equipment.

The placement/height of the hot wire is also very important. It should be attached at two-thirds the height of the animal to be controlled. Two offset wires, can and often are placed on the same fence. On one side a wire is placed at 30" to contain cattle, on the other side a wire is placed at 8" to repel predators.

As simple as it is, offset fencing still must be viewed as a system. One short cut, or one substandard component can destroy the effectiveness of the fence.



3. Temporary & Portable Fencing

A temporary/portable electric fence can be powered by any Gallagher Solar or Battery Energizer or can be simply connected to a permanent electric fence supplied by a 110v

powered Energizer.

As portable fencing is so easy to move and set up it's a versatile solution for fencing any type of animal, even on the most remote area of your property.


Once you've chosen your products, see below for the basics you'll need for portable fencing and the recommended fence set up for cattle, sheep, pigs, goats and horses.

Fence Set Up

Reels hold the tape, braid or wire for the portable fence. You can use just one reel for single line fences or up to three reels, attached to a reel stand, for multi-wire fences.

Posts are lightweight yet sturdy. Pigtail and Ring Top posts are most popular for cattle fences.

Multi-wire treadins are used for all other animals.



*Note: Wire spacing will differ depending on the type of post used.

Power Connectors

are leads that connect a portable fence to an existing permanent electric fence.

Tapes, Wires and Braids are used on portable fences rather than the galvanized wire used on permanent fences. Gallagher conductors are ideal for portable electric fences as they are light, visible and easy to wind.



The multiple lugs on Multi-wire Treadins allow attachment of a number of wires at different heights to accommodate a variety of animal types.



Ring Top Posts are a popular choice for cattle farmers. A single electrified wire is sufficient to contain even the most temperamental animals.



The Smart Fence 2, is an all-in-one portable fence. This instant fence system combines posts, reels and wire in one easily transportable package.

Temporary & Portable Fencing

Wire Selection

			FENCE VOLTAGE				
Conductor Selection Chart			328' FENCE	1,640' FENCE	3,280' FENCE	RESISTANCE (Ohms/mile)	MIXED METALS*
Braid, Wire, Rope	Turbo Braid - 3/16" G62174 656', White G62176 1,312', White	<ul style="list-style-type: none">9 Mixed metal strandsMost user-friendly for horse fencing - visible and safeBest suited for any distance temp or permanent fence	8kV	7.5kV	7.1kV	125	▪
	Turbo Braid - 7/64" G62148 1,312', White /Blue	<ul style="list-style-type: none">9 Mixed metal strandsSuperior heavy duty strength	8kV	7.5kV	7.1kV	125	▪
	Turbo Wire G62054 656' G620564 1,312' G62089 2,624'	<ul style="list-style-type: none">9 Mixed metalsBest suited to distances more than 1/4 mile, where extreme power is required40 times more conductive than standard Poly Wire	8kV	7.5kV	7.1kV	130	▪
	Poly Wire G62004 656' G620300 1,640'	<ul style="list-style-type: none">6 Stainless steel strandsBest suited for distances under 1/4 mile	5kV	2kV	1kV	6,000	
.5" Tape	.5" Turbo Tape G62354 656' G62356 1,312'	<ul style="list-style-type: none">Mixed metals 30x's more conductiveBest suited for distances greater than 1/4 mile	7.8kV	7.1kV	6.4kV	250	▪
	.5" Poly Tape G62304 656'	<ul style="list-style-type: none">6 Stainless steel strands for good conductivity	4.3kV	1.5kV	0.8kV	8,500	

* recommended for horses

Wire

Preferable where wind and adverse weather conditions exist.

Braid

Braided construction is designed not to tangle or overstretch adding durability.

Tape

Generally used where visibility is most important.

Temporary & Portable Fencing

Wire Selection

Understanding Wire

There are a number of different types of portable electric fence wires, tapes and braids - frequently called "conductors". Knowing which one to choose can be a bit tricky - especially for those new to electric fencing.

The most common portable/temporary fence "conductor" is what is called Poly Wire. Poly Wire is made of plastic strands and embedded thin metal wires used to carry electrical current from a Fence Charger/Energizer. The individual strands of plastic and wire are typically twisted tightly together to form a single wire.

A second option is Poly Tape. Poly Tape threads individual strands of plastic and wire together creating what appears to be a highly visible ribbon. Tape while prone to wind and ice damage, is the most visible "conductor" and is best used in situations where maximum visibility is needed. Poly Tape comes in different width sizes, but the most common are 1/2" and 1 1/2".

A third option is Poly Braid. Poly Braid is thicker and more visible than Poly Wire, and is less likely to be damaged by the wind and ice than Poly Tape.

Poly Braid consists of individual strands of plastic and wire that are braided together to form a tight weave making it more durable, and less prone to tangles and overstretching. Poly Braid comes in a number of different diameters (thickness).


Turbo products are always the best choice for distances beyond 1/4 mile where dependable power is required.

Electrical Connections

It is important to have good conductivity through the connection when you join wire or tape.

To do this, separate the metal strands by melting a strip of plastic threads with a match or lighter approximately 2" from the ends of each length. Pull the end off the plastic being careful not to break the steel wires. Tie both ends of the wire/tape together and then twist the steel wires together.

To join 1 1/2" Tape use a Tape Joiner. These also give good electrical contact.



Temporary & Portable Fencing

Difference between Turbo and Poly Products

So what is Turbo Wire and how is it different from Poly Wire?

Turbo products come in the same wire, tape and braided construction previously described for Poly - with one major difference. Turbo products have 9 strands of conductive metals including copper which make them up to 48X's more conductive than Poly products which only have 6 strands of stainless steel. This means with Turbo, your voltage will stay strong and carry a "shock" further down your fence line than Poly products. Long temporary fences (over 1/4 mile) should always be constructed from Turbo products to ensure maximum livestock control.

Why is copper so important?

Some metals conduct power better than others. Metals that are good conductors are said to have low resistance and metals which are not good conductors have high resistance. Copper happens to be a very low resistance conductor which enables Turbo products to carry power further down the fence line than Poly products. The copper wires in Gallagher's Turbo products are tin coated. This is why if you pull the plastic and metal strands apart, you will not see copper colored wires. The advantages of tinned copper over a non-tinned copper wire is greater longevity. Copper coated in tin is less susceptible to corrosion and even more conductive!

What does it mean that "Turbo is 48X's more conductive than Poly"?

What this means is that if you built two different fences .6 miles long and one was a single strand of Poly Wire and the other was a single strand of Turbo Wire - both fences would read 8,000 volts at the start; however, at the end of the fence you would only read 600 volts on the Poly Wire fence and the Turbo Wire fence would read 6,300 volts.

The resistance of a "conductor" (wire/tape/braid) is measured in Ohms. The lower the resistance, the more conductive the wire/tape/braid will be. As you can see from the values below, Turbo Wire is 48 times more conductive than Poly Wire.

Turbo Wire - 209 Ohms/mile
Poly Wire - 10,000 Ohms/mile

Temporary & Portable Fencing

Fence Posts

Portable Fence Posts

When installing a temporary fence, there are many durable, portable fence post options available.

Many portable fence posts come with a step-in feature. At the base of a step-in post, there is a footplate that allows you to push the post into the ground with your foot. This is a convenient feature so you won't need to drop your bundle of posts in order to pound them into the ground.

Other factors to consider are visibility, durability and the ability to add multiple wires for the animal needing to be fenced. Weather also influences selection as posts are much more difficult to insert into frozen ground.

Plastic Posts

Plastic step-in posts with built-in treads are convenient because they have pre-molded loops for multiple wires at various heights. Plastic posts are made from a heavy duty, UV-resistant polymer plastic and have a steel foot.

Metal Posts

Metal step-in pigtail posts are also available. These posts get their name from the curl loop that holds the wire and looks similar to a pig's tail.

Gallagher's Ring Top posts have a very high strength plastic head and foot coming in both a standard and heavy duty model.

Gallagher's Ring Top post while similar to the Pigtail, has a ring shaped nylon head that prevents wear and reduces tangles. The post's glass reinforced nylon footplate is strong and will not bend.

While both pigtail and ring top posts are designed for a single wire, plastic rod post insulators can be attached to the posts so additional wires may be added.

Fiberglass Posts

Fiberglass rods are better for situations when the fence is not going to be moved as often because these have to be pounded into the ground. These rods require the use of wire clips or plastic insulators that slide on the rod to hold the wire in place.

Rolling Posts

The Tumblewheel enables you to quickly and easily roll a fence line to a new position. The Tumblewheel's unique center hub maintains power while the fence is being moved. It can be used on flat very hard and frozen ground. The legs remain live except for two legs that are on the ground.

Where several breaks are needed in one paddock, Tumblewheels are ideal for quick and efficient rationing of grass. We recommend spacing at every 66'.

This fence consists of a number of electrified 'wheels' spaced across the pasture. The wheels are held upright with the tension of the single line fence which passes through the center.

When one or both ends of the fence is moved, the wheels roll along. When you stop, the fence stops.

Multi Wire Ring Top Post

Temporary & Portable Fencing

Reel and Gate Selection

Reels

Reels are an absolutely essential component of your portable electric fencing equipment.

They are designed to hold your wire, braid or tape and make it extremely quick and easy to roll up your temporary cross-fences.

Gallagher's geared reel comes with a locking device allowing for secure attachment to an ATV or fence wire. Geared reels also have a 3:1 ratio which means for each turn of the handle, the bobbin spins three times allowing you to wind your wire three times faster with each turn of the handle.

Geared reels are designed to hook the spool in place so it does not unravel. The hook allows you to hang the reel off of your permanent high-tensile electric fence.

An alligator clamp (also called a lead connector) is used to create a good electrical connection between the portable electric fence and your permanent electric fence.



Use an insulated handle on the far end of your portable electric fence so the fence is only powered from one side (at the geared reel). This ensures that the portable fence loses power once you disconnect the alligator clamps and geared reel so you can roll up the wire without getting shocked.


When rewinding long lengths of poly/turbo wire, braid and tape, the geared reel is a worthwhile, time-saving investment.

Temporary Gates

Give advance thought to the location of gate openings in your fence where people, animals and equipment need easy access to roads, structures or pastures.

Electrified gates are made from the same type of wire as the material used in your fence line. The number of gate strands should match the number of lines in your fence.

For easy assembly, consider using Gallagher's gate kits specific to the type of post or wire you are using. Our kits



include the handle, insulators, hardware and simple installation instructions.

3-Way Gate Anchors as seen in the diagram above, make it easy to attach gate handles to the post and are worth the investment.

Temporary & Portable Fencing

Single Wire Construction

Portable Fence Construction

Reels holding wire/tape can be used individually for single line fences or for up to three lines using three reels attached to a reel stand.

Single Wire Fence:

1. Hook the reel to the anchor point (e.g.: permanent fence/reel stand) and disengage the ratchet.
2. Carrying the insulated handle and sufficient portable posts, walk along the proposed line allowing the reel to unwind and connect to the other end.
3. Walk back to the reel, placing a post every 66' (or closer on uneven ground) and locate the wire/tape in the post.
4. At the end of the fence, engage the ratchet and tension the wire.
5. Connect to power – either connect to the permanent fence by connecting leadset to both powered permanent fence line and the portable wire or using a solar or battery Energizer.
6. When you remove the fence, do the same process in reverse.

CAUTION

Do not wind the conductor through the posts as the abrasion will damage the post.



Temporary & Portable Fencing

Multi-Wire Construction

Multi-wire Fence

1. Attach the required reels to a reel stand & chain the reel stand to an anchor point.
2. Hook the insulated handles through the head/lug of the first post to prevent them becoming twisted.
3. Follow steps 2-6 above only this time with multiple lines together not one single one.

Note – place posts every 33-40' and use a multi-reel lead connector if using a battery Energizer.

All in one multi-wire portable fence system

A quicker and easier all in one instant fence system, the Smart Fence System includes 4 wires, 10 posts, 328' length. Energizer is sold separately.



Safety

Here are some safety considerations to follow when installing electric fencing:

1. Only connect one energizer to a fence.

2. There is a misconception that dry vegetation touching an electric fence can cause fires – this is extremely unlikely. In order to create a short, vegetation needs to be damp or green so therefore the vegetation will not ignite. Once vegetation dries out it becomes non-conductive meaning any short created disappears.


The only conceivable but still very unlikely scenario where an electric fence could start a fire is when a wire shorts to an grounded metal object, such as a steel post or wire where insulators have broken, in the presence of abundant dry vegetation. This scenario is very unlikely to occur in practice, and even less so on a well-maintained fence.

Producers with fences on steel posts or those using grounded wires in the fence are advised to ensure the live wires are well insulated and the fence is clear of vegetation. If these factors are of concern then on days of severe or above fire risk, consider turning the energizer off.

3. Ground rods for energizers should be at least 65' from utility grounding fields.

4. Avoid running fences parallel to power lines, and try to install fences so that they cross power lines at right angles. If you can't avoid parallel electric fences and power lines, offset the fences at least 30 feet from the power lines, and make sure the top fence wires are no more than six feet high.

5. Do not attach fence wires to utility poles.



6. Electric fences bordering public thoroughfares are required to have a warning sign at least every 295' feet where the public has access to electric fences, such as along roads.

Check with your local authority for specific regulations.

7. Landowners are responsible for preventing audible interference with telephone lines. Therefore, try to avoid installing electric fences under telephone wires, and minimize the distance that electric fence wires run parallel to underground telephone cables.

This particularly applies if the electric fence wire is carrying high current, such as a leadout wire to a large fencing system.

8. Don't touch fences with your head or mouth. People with pacemakers or other heart problems also should consult their doctors before working with or near electric fences. Always use precautions.

9. Never use barbed wire for electric fence wire because people or animals could more easily become entangled in it.

10. Keep electric fences as far away from radio antennas as possible. Gallagher energizers comply with usual Telecom and International standards and safety regulations. However, problems can arise for a number of reasons and can be difficult to eliminate in areas with poor radio reception.

To avoid radio interference:

- The energizer ground must be highly conductive
- The energizer must be well away from any electrical power supply
- The energizer should be well away from any water pipes

Do not allow an energizer ground wire to touch a building which can act as a broadcast aerial. Use proper leadout cable to insulate the ground wire. Ground the offending radio and improve its aerial. Try to keep both as far away from the energizer and fence lines as possible.

All types of wire may break and recoil when stretched. Always use hand and eye protection when handling hi-tensile wire.



Troubleshooting

Common electric fencing issues & solutions

#1 Energizer is not on or there is no volt meter reading across the energizer output terminals with the energizer disconnected from the fence.

Potential Causes:

1) Mainline power outage or blown fuse on input circuit
Solution: Restore power or replace blown fuse

2) Energizer is switched off
Solution: Check energizer "on-off" switch.

3) Dry cell batteries are dead; wet cell batteries are discharged
Solution: Recharge or replace batteries

4) Battery terminals are corroded
Solution: Clean terminals

5) Energizer is faulty
Solution: Have energizer serviced

#2 Energizer is on, but volt meter reading is low across the energizer output terminals when disconnected from fence.

Potential Causes:

1) Energizer is switched to "low" setting
Solution: Check energizer output switch

2) Weak batteries
Solution: Recharge or replace batteries

3) Battery terminals are corroded
Solution: Clean battery terminals
Troubleshooting

#3 Energizer is operating, but there is no volt meter reading on the fence with the energizer connected

Potential Causes:

1) Ground-return wire is disconnected or broken
Solution: Connect or repair ground-return wire

2) Feed-wire terminals are corroded, disconnected or broken
Solution: Connect or repair feed wire terminals

3) Probable Cause: Broken, corroded or disconnected live wire or ground-return on fence
Solution: Connect or repair live wire or ground-return on fence

4) Soil is dried out
Solution: Install ground-return wire

#4 Low volt meter readings at several locations on fence

Potential Causes:

1) Energizer is on low setting or is inadequate for length of fence
Solution: Switch energizer to high setting; install more powerful unit

2) Weak batteries
Solution: Recharge or replace batteries

3) Terminals corroded
Solution: Clean terminals

4) Ground system is inadequate or deteriorated
Solution: Repair or replace ground system

5) Soil is dried out
Solution: Install ground-return wire

Troubleshooting

#5 No volt meter readings at several locations on fence

Potential Causes:

- 1) Broken or disconnected fence wire, jumper wire or ground wire
Solution: Connect or repair wire; remove cause of short; replace jumper connection
- 2) Broken or faulty insulators
Solution: Replace faulty insulators
- 3) Ground connection rod deteriorated
Solution: Replace ground connection rod

#6 Volt meter reading on one wire is higher than on another wire, or there is no reading from one live wire to ground-return or soil

Potential Causes:

- 1) Broken or disconnected fence wire, jumper wire or ground wire
Solution: Connect or repair wire; remove cause of short; replace jumper connection
- 2) Broken or faulty insulators
Solution: Replace faulty insulators
- 3) Ground connection rod deteriorated
Solution: Replace ground connection rod

#7 Radio, TV or telephone interference

Potential Causes:

- 1) Ground system inadequate
Solution: Increase grounding capacity
- 2) Antenna too close to fence
Solution: Relocate antenna or telephone wires
- 3) Fence is parallel with antenna wires or telephone lines
Solution: De-electrify or relocate segment of fence that is parallel to or too close to antenna or wires

Troubleshooting

Common faults to look for and fix:

- Poor connections at the rods, ground return wire or in the connecting wire
- Rusty or corroded ground rods
- Not enough ground rods (on a ground return wire system rods can be installed at various places around the fencing system & connected to the ground return wire)
- Broken ground wire connecting the rods
- Rods too close together or too short

Searching for a fault

A short is a fault somewhere on the fence that has caused it to lose power. The most common types are vegetation overgrowth, loose wires and broken insulators.

Gallagher has some great tools for testing and finding these quickly and easily.

- Fault Finder – shows voltage, current and direction of fault
- Fence Volt Meter – a digital read out of the voltage at that point on the fence
- Live Fence Indicator – sits on your fence line and flashes with each pulse over 2kV so you can see from a distance

To trace a fault using a volt meter travel along the fence line and check the voltage about every 330'. If the short is serious, the voltage will continue to fall until the fault is reached. If the fault is passed the voltage will remain fairly constant. You should then backtrack to find it. At fence junctions isolate different fences with a Cut Out Switch.

Using a Fault Finder

1. Put the Fault Finder into current measurement mode
2. Place it on the fence with the wire in the measurement slot and making good contact with the contact plate.
3. The arrow on the LCD display will indicate which direction the current is flowing. The amount of Amps will show on the display. The higher the number, the bigger the fault.

Progress as above. If the current reading drops significantly the fault is back towards your previous reading. The process is similar to finding water leaks, where the Fault Finder is reporting the amount and direction of the flow.

Induction


Induction is the transfer of voltage from a live wire to a neutral wire by electromagnetic rather than direct physical contact.

If you are getting a small shock from “non-live” wires or steel gates, particular in dry weather, this is likely to be caused by induction. Neutral wires (neither live nor ground) can be charged from live wires (usually leadout or offset wires), running in parallel. It is not a short and will not reduce fence voltage.

To remove the problem, ground out the offending wires by pushing a heavy gauge galvanized wire as far as possible into the ground next to the strain post and staple it across the offending wires. This will not reduce the voltage on the insulated powered wires.

Troubleshooting

If you find there is not enough power on your fence follow the chart below to find the most common causes.





GALLAGHER NORTH AMERICA

5005 NW 41st Street Riverside, MO 64150
info.usa@am.gallagher.com

am.gallagher.com

01/2025